

THE MICRO PHASE COMMUNICATION MP-9202 L-BAND UP CONVERTER SPECIFICATIONS

Input Characteristics

Frequency Range	70 ± 20MHz 140 ± 40MHz (optional)
Impedance	75Ω (50Ω optional)
Return Loss	>26dB

Output Characteristics

Frequency Range	950 - 1750MHz
Step Size	125kHz
Impedance	50Ω
Return Loss	>15dB

Transfer Characteristics

Conversion Gain	30dB
Gain Flatness	±0.5dB (950 to 1750MHz)
Amplitude Flatness	±0.35dB (70 ± 20MHz) ±0.35dB (140 ± 40MHz)

Attenuator Range	0 to 30dB (continuous)
Attenuator Resolution	0.1db

Gain Stability: Over 24hrs at constant temp 0°C to +50°C	±0.25dB ±0.35dB
--	--------------------

<u>Phase Noise (SSB)</u>	
100Hz	75dBc
1 kHz	89dBc
10kHz	90dBc
100kHz	100dBc

Third Order Intermod Distortion:

Output (full gain)	-40dBc @ 0dBm output per ckr
Output 1dB Compression	0dBm @ 30dB Gain

Group Delay:

Linear	0.06ns/MHz
Parabolic	0.015ns/(MHz) ²

Spurious:

Carrier Dependent	-70dBc at full gain
Carrier Independent	-70dBm at full gain

Image Rejection:

1st Mixer	-75dBc (out of band)
2nd Mixer	-75dBc (in band)

Mute	-80dBc
------	--------

Reference

Frequency	10MHz
Frequency Stability	5 x 10 ⁻⁹ from 0 to 50°C
<u>Frequency Aging:</u>	±5 x 10 ⁻¹⁰ per day ±1 x 10 ⁻⁷ per year
Warmup	±1 x 10 ⁻⁷ after 2.5min @ 25°C

Front Panel

Display	LCD 2 x 40 Character (Backlit)
Data Entry	Keyboard
Indicators	Power, Alarm, Remote, Ext Ref
Monitor Points	IF (BNC Female) LO (BNC Female)

Rear Panel

RF Output	BNC Female (type N optional)
RF Input	BNC Female
Internal Reference Output	BNC Female
Ext Reference Input	BNC Female (5MHz or 10MHz)

Remote Control:

RS232	9-pin D Male
RS485	9-pin D Male
Summary Alarm	9-pin D Female (Form-C Relay)

Miscellaneous

Remote Control	All Front Panel Functions Full Status Reporting
----------------	--

External Reference:

5/10MHz auto detect and locking of Internal 10MHz Reference
Lock Range ±5 x 10 ⁻⁷

General

Size	13.5" D x 19" W x 1.75" H
Weight	13lbs
Power Consumption	30W max
Voltage	100-240VAC 50/60Hz
Temperature	0 to 50°C

Related Products

MP-9201	L-Band Downconverter
MP-9240	C-Band Downconverter
MP-9260	C-Band Upconverter